

**DIGITAL SIGNAL PROCESSING**

(Common to ECE and EIE)

Time: 3 hours

Max. Marks: 70

**PART – A**  
(Compulsory Question)

\*\*\*\*\*

- 1 Answer the following: (10 X 02 = 20 Marks)
- Define energy & power signals.
  - Consider a finite duration sequence  $X(n) = \{2, 4, 0, 3\}$ . Resolve the sequence into sum of weighted impulses.
  - What is FFT?
  - Draw the direct form-II realization of two pole resonator from Goertzel algorithm.
  - Define signal flow graph.
  - Draw the direct form-I realization structure of IIR filter.
  - What is realization.
  - Distinguish between Recursive & non recursive realization.
  - Define the terms decimation and Interpolation.
  - What are the applications of multi rate signal processing?

**PART – B**

(Answer all five units, 5 X 10 = 50 Marks)

**UNIT – I**

- 2 Explain about classification of discrete time systems briefly.
- OR**
- 3 (a) Discuss about linearity, periodicity properties of DFT.  
(b) Perform circular convolution of two sequences given by  $X_1(n) = \{1, 2, 3, 4\}$   $X_2(n) = \{-1, 3, -5, 7\}$ .

**UNIT – II**

- 4 Implement the decimation in time FFT algorithm for  $N = 16$ .
- OR**
- 5 Write short notes on the following: (i) Split-radix FFT. (ii) Applications of Goertzel algorithm. (iii) Quantization errors. (iv) Radix -4 FFT Algorithm. (v) Chirp-Z transforms.

**UNIT – III**

- 6 Obtain the direct form-I, direct form-II, cascade and parallel realization for the following system:  
 $Y(n) = -0.1y(n-1) + 0.2y(n-2) + 3x(n) + 3.6x(n-1) + 0.6x(n-2)$
- OR**

- 7 (a) Determine the direct form-II and transposed direct form –II for the given system:  
 $Y(n) = \frac{1}{2}y(n-1) - \frac{1}{4}y(n-2) + x(n) + x(n-1)$   
(b) An FIR filter is given by the difference equation:  
 $y(n) = 2x(n) + \frac{4}{5}x(n-1) + \frac{3}{2}x(n-2) + \frac{2}{3}x(n-3)$ . Determine its Lattice form.

**UNIT – IV**

- 8 Design a digital Butterworth filter satisfying the following constrains:  
 $0.707 \leq |H(e^{j\omega})| \leq 1$  for  $0 \leq \omega \leq \pi/2$   
 $|H(e^{j\omega})| \leq 0.2$  for  $3\pi/2 \leq \omega \leq \pi$   
With  $T = 1$ sec using bilinear transformation.
- OR**

- 9 Design a filter with:  
 $H_d(e^{j\omega}) = e^{-j3\omega}$   $-\pi/4 \leq \omega \leq \pi/4$   
 $= 0$   $\pi/4 < \omega \leq \pi/4$  using Hamming window with  $N = 7$ .

**UNIT – V**

- 10 Sketch the following signals:  
 $X_1(n) = n, n > 0$   
 $= 0$  otherwise  
 $X_2(n) = n^2, n > 0$   
 $= 0$  otherwise

Also sketch decimated and interpolated version of above systems with a factor of '2'.

**OR**

- 11 With the help of block diagram explain in detail about multistage implementation of sampling rate conversion by rational factor  $I/D$ .

\*\*\*\*\*