

II B. Tech I Semester Regular/Supplementary Examinations, October/November - 2019
ELECTROMAGNETIC FIELDS
 (Electrical and Electronics Engineering)

Time: 3 hours

Max. Marks: 70

- Note: 1. Question Paper consists of two parts (**Part-A** and **Part-B**)
 2. Answer **ALL** the question in **Part-A**
 3. Answer any **FOUR** Questions from **Part-B**

PART -A

1. a) State Gauss Law. (2M)
- b) Write the difference between convection current density and conduction current density. (2M)
- c) State Ampere's circuit law. (2M)
- d) Compare electric force and magnetic force. (3M)
- e) Define coefficient of coupling. (2M)
- f) Write Maxwell's equations in point form. (3M)

PART -B

2. a) Derive the expression for electric field intensity due to sheet of charge. (7M)
- b) Explain about Poisson's equation and Laplace equation. (7M)
3. a) Derive the expression for capacitance of parallel-plate capacitor. (7M)
- b) An electric dipole located at the origin in free space has a moment $\mathbf{p} = 3\mathbf{a}_x - 2\mathbf{a}_y + \mathbf{a}_z$ nC.m. (i) Find V at P(2, 3, 4) (ii) Find V at $r = 2.5$, $\theta = 30^\circ$, $\phi = 40^\circ$. (7M)
4. a) Derive the expression for magnetic field intensity due to infinitely long straight filament carrying a direct current I. (7M)
- b) Explain about magnetic flux and magnetic flux density. (7M)
5. a) Explain the concept of magnetic dipole. (7M)
- b) A charged particle of mass 1 kg and charge 2 C starts at the origin with zero initial velocity in the region where $\mathbf{E} = 3\mathbf{a}_z$ V/m. Find (7M)
 - (i) the force on the particle
 - (ii) the time it takes to reach point P(0, 0, 12m)
 - (iii) Its velocity and acceleration at P.
6. a) Obtain an expression for the self-inductance of a toroid of circular cross section with 'N' closely spaced turns. (7M)
- b) A solenoid with length 10 cm and radius 1 cm has 450 turns. Calculate its inductance. (7M)
7. a) A parallel plate capacitor with plate area of 5 cm^2 and separation of 3 mm has a voltage $50 \sin 10^3 t$ V applied to its plates. Calculate the displacement current assuming $\epsilon = 2\epsilon_0$. (7M)
- b) Explain about Dynamically induced EMFs. (7M)

II B. Tech I Semester Regular/Supplementary Examinations, October/November - 2019
ELECTROMAGNETIC FIELDS
 (Electrical and Electronics Engineering)

Time: 3 hours

Max. Marks: 70

- Note: 1. Question Paper consists of two parts (**Part-A** and **Part-B**)
 2. Answer **ALL** the question in **Part-A**
 3. Answer any **FOUR** Questions from **Part-B**

PART -A

1. a) Write Laplace equation in both Cartesian and cylindrical coordinates. (2M)
- b) Calculate the capacitance of a parallel plate capacitor having a mica dielectric, $\epsilon_r = 6$, a plate area of 10 in^2 , and a separation of 0.01 in . (3M)
- c) Define magnetic flux density. (2M)
- d) Define magnetic dipole moment. (2M)
- e) Define internal inductance and external inductance. (2M)
- f) Write Maxwell's equations in integral form. (3M)

PART -B

2. a) State and explain coulomb's law with necessary equations. (7M)
- b) Find the electric field intensity at $P(1,1,1)$ caused by four identical 3 nC charges located at $P_1(1,1,0)$, $P_2(-1,1,0)$, $P_3(-1,-1,0)$ and $P_4(1, -1, 0)$. (7M)
3. a) Derive the expression for capacitance of a spherical capacitor. (7M)
- b) An electric dipole of $100 \text{ a}_z \text{ pC.m}$ is located at the origin. Find V and E at points (i) $(0, 0, 10)$ and (ii) $(1, \pi/3, \pi/2)$ (7M)
4. a) A square conducting loop 3 cm on each side carries a current of 10 A . Calculate the magnetic field intensity at the center of the loop. (7M)
- b) Using Ampere's circuit law, determine the expression for H due to uniform sheet of surface current $K = K_y \text{ a}_y$ in the $z = 0$ plane. (7M)
5. a) Discuss about force between differential current elements. (7M)
- b) Explain about torque on a current loop placed in magnetic field. (7M)
6. a) A long solenoid with length l and a radius R consists of N turns of wire, a current I passes through the coil. Find the energy stored in the system. (7M)
- b) Calculate the self inductances of and the mutual inductances between two coaxial solenoids of radius R_1 and R_2 , $R_2 > R_1$, carrying currents I_1 and I_2 with n_1 and n_2 turns/m, respectively. (7M)
7. a) In free space $E = 20 \cos(\omega t - 50x) \text{ a}_y \text{ V/m}$. calculate (i) J_d (ii) H (c) ω (7M)
- b) State and explain poynting theorem. (7M)

II B. Tech I Semester Regular/Supplementary Examinations, October/November - 2019
ELECTROMAGNETIC FIELDS
 (Electrical and Electronics Engineering)

Time: 3 hours

Max. Marks: 70

- Note: 1. Question Paper consists of two parts (**Part-A** and **Part-B**)
 2. Answer **ALL** the question in **Part-A**
 3. Answer any **FOUR** Questions from **Part-B**

PART -A

1. a) Find div **D** at the origin if $\mathbf{D} = e^{-x} \sin y \mathbf{a}_x - e^{-x} \cos y \mathbf{a}_y + 2z \mathbf{a}_z$. (3M)
- b) What is meant by boundary conditions? How they are useful? (2M)
- c) Plane $y = 0$ carries a uniform current of $30 \mathbf{a}_z$ mA/m. Determine the magnetic field intensity at (1, 10, -2). (3M)
- d) Write Lorenz force equation. (2M)
- e) Define self inductance. (2M)
- f) What is poynting vector? (2M)

PART -B

2. a) State and explain Gauss law. Write the applications of it. (7M)
- b) A charge of $-0.3 \mu\text{C}$ is located at A(25, -30, 15) (incm) and a second charge of $0.5 \mu\text{C}$ is at B(-10, 8, 12) cm . Find E at (a) the origin (b) P(15,20, 50) cm. (7M)
3. a) Discuss about behavior of conductors in an electric field. (7M)
- b) Derive the expression for energy density in electrostatic field. (7M)
4. a) Determine **H** at P(0.4, 0.3, 0) in the field of an 8-A filamentary current directed inward from infinity to origin on the positive x axis, and then outward to infinity along the y axis. (7M)
- b) Using ampere's circuit law, determine the magnetic field intensity due infinitely long coaxial transmission line. (7M)
5. a) Explain about force on a differential current element. (7M)
- b) Derive the expression for magnetic field produced by magnetic dipole. (7M)
6. a) Explain about Mutual Inductance between two coupled inductors. (7M)
- b) A very long solenoid with 2 X 2 cm cross section has an iron core ($\mu_r = 1000$) and 4000 turns/meter. If it carries a current of 500 mA, find
 (i) Its self-inductance per meter
 (ii) The energy per meter stored in its field. (7M)
7. a) Explain about Faraday's laws of electromagnetic induction. (7M)
- b) In air, $\mathbf{E} = \frac{\sin \theta}{r} \cos(6 \times 10^7 t - \beta r) \mathbf{a}_\phi$ V/m. Find β and **H**. (7M)

II B. Tech I Semester Regular/Supplementary Examinations, October/November - 2019
ELECTROMAGNETIC FIELDS
 (Electrical and Electronics Engineering)

Time: 3 hours

Max. Marks: 70

- Note: 1. Question Paper consists of two parts (**Part-A** and **Part-B**)
 2. Answer **ALL** the question in **Part-A**
 3. Answer any **FOUR** Questions from **Part-B**

PART -A

1. a) Define electric field intensity. (2M)
- b) Write the equation of continuity. (2M)
- c) Write Maxwell's second equation. (2M)
- d) What is ampere's force law? Explain. (3M)
- e) Define mutual inductance. (2M)
- f) What is displacement current? (3M)

PART -B

2. a) Determine an expression for the volume charge density associated with each **D** field following: (7M)
 (i) $\mathbf{D} = \frac{4xy}{z} \mathbf{a}_x + \frac{2x^2}{z} \mathbf{a}_y - \frac{2x^2y}{z^2} \mathbf{a}_z$; (ii) $\mathbf{D} = z \sin\phi \mathbf{a}_\rho + z \cos\phi \mathbf{a}_\phi + \rho \sin\phi \mathbf{a}_z$
- b) What is potential gradient? Explain. (7M)
3. a) Define electric dipole. Derive the expression for electric field due to electric dipole. (7M)
- b) Derive the boundary conditions of electric field for perfect dielectric materials. (7M)
4. a) State and explain Biot-savart's law. (7M)
- b) Derive the expression for magnetic field intensity due to an infinite line current using Ampere's circuit law. (7M)
5. a) Discuss about Force on a moving charge due to electric field and magnetic field. (7M)
- b) A charged particle moves with a uniform velocity $4\mathbf{a}_x$ m/s in a region where $\mathbf{E} = 20 \mathbf{a}_y$ V/m and $\mathbf{B} = B_0 \mathbf{a}_z$ Wb/m². Determine B_0 such that the velocity of the particle remains constant. (7M)
6. a) Derive the expression for energy in a magnetostatic field. (7M)
- b) Calculate the self inductance per unit length of an infinitely long solenoid. (7M)
7. a) Explain about Statically induced EMFs. (7M)
- b) A conducting circular loop of radius 20 cm lies in the $z = 0$ plane in a magnetic field $\mathbf{B} = 10 \cos 377 t \mathbf{a}_z$ mWb/m². Calculate the induced voltage. (7M)