

Total No. of Questions : 8]

SEAT No. :

**P3504**

[5560]-154

[Total No. of Pages : 2

**T.E. (Electronics and Telecommunication)**  
**ELECTROMAGNETIC AND TRANSMISSION LINES**  
**(2012 Course) (Semester-I) (304181)**

*Time : 2½ Hours]*

*[Max. Marks : 70*

*Instructions to the candidates:*

- 1) Answer Q1 or Q2, Q3 or Q4, Q5 or Q6, Q7 or Q8.
- 2) Neat diagrams must be drawn wherever necessary.
- 3) Figures to the right side indicate full marks.
- 4) Use of calculator is allowed.
- 5) Assume suitable data if necessary.

- Q1)** a) Derive the expression for electric field intensity  $\vec{E}$  for infinite sheet of charge. [8]
- b) Find the current crossing the portion of  $y = 0$  plane defined by  $-0.1 \leq x \leq 0.1$  m and  $-0.002 \leq z \leq 0.002$  m if  $\vec{J} = 10^2 |x| \hat{ay}$  where  $\vec{J}$  is the current density. [6]
- c) State and explain Biot-Savart law. [6]

OR

- Q2)** a) Derive boundary condition between conductor and free space. [8]
- b) A point charge of 5 nC is located at the origin. If  $V=2$  V at  $(0,6,-8)$ , Find [6]
- i) The potential at A  $(-3, 2, 6)$
  - ii) The potential at B  $(1, 5, 7)$
  - iii) Potential difference  $V_{AB}$
- c) State and prove Stoke's theorem [6]

- Q3)** a) What is Poynting theorem? What is its significance? Derive the equation for Poynting Theorem. [10]
- b) Calculate the displacement current through parallel plate air filled capacitor having plates of area  $10 \text{ cm}^2$  separated by a distance 2 mm connected to 300V, 1 MHz. [8]

OR

*P.T.O.*

**Q4)** a) What do you mean by uniform plane wave? Obtain equation of wave travelling in free space in terms of  $\vec{E}$ . [10]

b) In free space,  $\vec{E} = 50 \cos(\omega t - \beta z) \hat{a}_x$  V/m. Find the average power crossing a circular area of radius 2.5 m in the plane  $z=0$ . Assume  $E_m=H_m \cdot \eta_0$  and  $\eta_0 = 120\pi \Omega$ . [8]

**Q5)** a) State primary and secondary constant of transmission line & hence derive relationship between primary & secondary constant of transmission line. [8]

b) The characteristics impedance of uniform transmission line is  $2040 \Omega$  at a frequency of 800 Hz. At this frequency, the propagation constant is  $0.054/-87.9^\circ$ . Find the values of R, L, G and C. [8]

OR

**Q6)** a) Derive the expression of characteristics impedance and propagation constant in terms of primary constant of transmission line. [8]

b) A transmission line has series inductance of 0.56 mH and capacitance of  $0.1 \mu F$  per km. If the losses due to conductor resistance and insulation leakage are negligible, calculate, [8]

- Characteristics impedance
- Phase velocity.

**Q7)** a) What do you mean by single stub matching on a line and derive the equation of single stub along the line. [8]

b) Design a quarter wave transformer to match a load of  $200 \Omega$  to a source resistance of  $500 \Omega$  at operating frequency of 200 MHz. [8]

OR

**Q8)** a) Explain the phenomena of reflection of transmission line and hence define reflection coefficient. [8]

b) Write and explain any 4 properties of smith chart. [8]

